

DESCRIPTION:	3 Monthly Zone 4 Lubrication Maintenance	FREQUENCY:	3 Monthly
LOCATION:	ST18 Luggage Point STP	STD JOB ID:	LTS021

	Grease and Oils Required	Maintenance Group
	Castrol AP3 Grease	MF Feed Pumps
	Castrol Hyspin AWS46	MF CIP Pumps
		MF Reverse Filtration Pump
		RO Feed Pumps
		RO Flushing Pumps
	References	RO CIP Pumps
		Product Water Pumps
	Procedural Steps	
	MF Feed Pump 1	
	Grease motor bearings while pump is running. Apply 2 shots of AP3 grease.	
	MF Feed Pump 2	
	Grease motor bearings while pump is running. Apply 2 shots of AP3 grease.	
	MF Feed Pump 2	
	Grease motor bearings while pump is running. Apply 2 shots of AP3 grease.	
	New MF Feed Pump no 3 does not require greasing or oil. Bearings greased and sealed for life.	
	MF CIP Tank Heater Pump 1	
	Grease motor bearings. Apply 2 shots of AP3 Grease.	
	Check pump's oil level. Top up if required with Hyspin AWS46.	
	MF Reverse Filtration Pump 1	
	Grease motor bearings. Apply 2 shots of AP3 Grease.	
	Grease pump's bearings. Apply 2 shots of AP3 Grease.	
	MF Reverse Filtration Pump 2	
	Grease motor bearings. Apply 2 shots of AP3 Grease.	
	Grease pump's bearings. Apply 2 shots of AP3 Grease.	
	RO Feed Pump 1	
	Grease motor bearings. Apply 2 shots of AP3 Grease.	
	Grease pump's bearings. Apply 2 shots of AP3 Grease.	

DESCRIPTION:	3 Monthly Zone 4 Lubrication Maintenance	FREQUENCY:	3 Monthly
LOCATION:	ST18 Luggage Point STP	STD JOB ID:	LTS021

RO Feed Pump 2
Grease motor bearings. Apply 2 shots of AP3 Grease.
Grease pump's bearings. Apply 2 shots of AP3 Grease.
RO Feed Pump 3
Grease motor bearings. Apply 2 shots of AP3 Grease.
Grease pump's bearings. Apply 2 shots of AP3 Grease.
RO Feed Pump 4
Grease motor bearings. Apply 2 shots of AP3 Grease.
Grease pump's bearings. Apply 2 shots of AP3 Grease.
RO Flushing Pump1
Grease motor bearings. Apply 2 shots of AP3 Grease.
Check pump's oil level. Top up if required with Hyspin AWS46.
RO Flushing Pump 2
Grease motor bearings. Apply 2 shots of AP3 Grease.
Check pump's oil level. Top up if required with Hyspin AWS46.
RO CIP Pump 1
Check pump's oil level. Top up if required with Hyspin AWS46.
Product Water Pump 1
Grease motor bearings while pump is running. Apply 2 shots of AP3 grease.
Product Water Pump 3
Grease motor bearings while pump is running. Apply 2 shots of AP3 grease.
Product Water Pump 3
Grease motor bearings while pump is running. Apply 2 shots of AP3 grease.